


< HIGH VOLTAGE DIODE MODULES >

RM800DG-90F


HIGH POWER SWITCHING USE INSULATED TYPE

High Voltage Diode Modules



APPLICATION

Traction drives, High Reliability Converters / Inverters, DC choppers



MAXIMUM RATINGS

Symbol	Item	Conditions	Ratings	Unit
V_{RRM}	Denotitivo peak reverse veltage	T _j = -40+125°C	4500	
	Repetitive peak reverse voltage	$T_j = -50^{\circ}C$	4400	V
I _F	Forward current	DC, $T_c = 65^{\circ}C$	800	Α
I _{FSM}	Surge forward current	T 405°C + 40 mg Holf sing ways V 0 V	6.5	kA
I ² t	Surge current load integral	T_{j_start} = 125°C, t_p = 10 ms, Half-sine wave, V_R = 0 V	211	kA ² s
P _{tot}	Maximum power dissipation	$T_c = 25$ °C	4160	W
V _{iso}	Isolation voltage	RMS, sinusoidal, f = 60 Hz, t = 1 min.	10200	V
V _e	Partial discharge extinction voltage	RMS, sinusoidal, f = 60 Hz, Q _{PD} ≤ 10 pC	3500	V
Tj	Junction temperature		− 50 ~ + 150	°C
T _{jop}	Operating junction temperature		− 50 ~ + 125	°C
T _{stg}	Storage temperature		− 55 ~ + 75	°C

ELECTRICAL CHARACTERISTICS

Comple at	ltere	Conditions		Limits			Linit	
Symbol	Item			Min	Тур	Max	Unit	
,	Donotiti va va va va a avvena t	V V	$T_j = 25^{\circ}C$	_		1.0	mA	
I _{RRM}	Repetitive reverse current	$V_{RM} = V_{RRM}$	$T_{j} = 125^{\circ}C$		3.0	_	IIIA	
	Converd voltage	I _E = 800 A	$T_j = 25^{\circ}C$	_	2.55	_	V	
V_{FM}	Forward voltage	I _F = 800 A	$T_j = 125^{\circ}C$		2.85	3.45		
	Davis and a second and time a		$T_j = 25^{\circ}C$	_	0.70	_		
t _{rr}	Reverse recovery time	V _{CC} = 2800 V	T _j = 125°C	_	0.90	_	μs	
	Deverse receivers current	I _F = 800 A	T _j = 25°C	_	700	_	Α	
Irr	Reverse recovery current			$T_j = 125^{\circ}C$	_	760	_	A
	Deverse receivery charge	$-d_i/d_t = 2600 \text{ A/µs } @ T_j = 25^{\circ}\text{C}$ $-d_i/d_t = 2400 \text{ A/µs } @ T_j = 125^{\circ}\text{C}$	T _j = 25°C	_	660	_		
Q_{rr}	Reverse recovery charge		T _j = 125°C	_	1040	_	μC	
_	(Note 1)	L _s = 150 nH Inductive load	T _j = 25°C	_	0.96	_		
E _{rec(10%)}	Reverse recovery energy (Note 1)		T _j = 125°C	_	1.50	_	J	
_	Reverse recovery energy		T _j = 25°C	_	1.10	_		
E _{rec}			T _j = 125°C	_	1.70	_	J	

THERMAL CHARACTERISTICS

Symbol	Itom	Conditions	Limits			Unit
	ltem		Min	Тур	Max	Unit
$R_{th(j-c)}$	Thermal resistance	Junction to Case (per 1/2 module)		_	30.0	K/kW
R _{th(c-s)}	Contact thermal resistance	Case to heat sink, $\lambda_{grease} = 1$ W/m·k $D_{(c-s)} = 100 \ \mu m$ (per 1/2 module)	_	24.0	_	K/kW

MECHANICAL CHARACTERISTICS

Symbol	ltem	Conditions	Limits			l lait
			Min	Тур	Max	Unit
M_t	Manustina tanana	M8 : Main terminals screw	7.0	_	22.0	N⋅m
Ms	Mounting torque	M6 : Mounting screw	3.0	_	6.0	N⋅m
m	Mass		_	1.0	1	kg
CTI	Comparative tracking index		600	_		_
d _a	Clearance		26.0	_	_	mm
ds	Creepage distance		56.0	_	1	mm
L _{P AK}	Parasitic stray inductance		_	22.0		nΗ
R _{AA'+KK'}	Internal lead resistance	$T_c = 25^{\circ}C$	_	0.14		mΩ


Note 1. Note 2.

 $E_{\rm rec(10\%)}$ are the integral of 0.1V_R x 0.1I_F x dt. Definition of all items is according to IEC 60747, unless otherwise specified.


RM800DG-90F HIGH POWER SWITCHING USE INSULATED TYPE

PERFORMANCE CURVES


FORWARD CHARACTERISTICS (TYPICAL)




REVERSE RECOVERY ENERGY CHARACTERISTICS (TYPICAL)



REVERSE RECOVERY CHARACTERISTICS (TYPICAL)




REVERSE RECOVERY SAFE OPERATING AREA (RRSOA)



RM800DG-90F HIGH POWER SWITCHING USE INSULATED TYPE

PERFORMANCE CURVES

TRANSIENT THERMAL IMPEDANCE CHARACTERISTICS



$$Z_{th(j-c)}(t) = \sum_{i=1}^{n} R_{i} \left\{ 1 - exp^{\left(-\frac{t}{\tau_{i}}\right)} \right\}$$

	1	2	3	4
R _i [K/kW]	0.0055	0.2360	0.4680	0.2905
t _i [sec]	0.0001	0.0131	0.0878	0.6247

Keep safety first in your circuit designs!

Mitsubishi Electric Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of non-flammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

- These materials are intended as a reference to assist our customers in the selection of the Mitsubishi semiconductor product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Mitsubishi Electric Corporation or a third party.
- Mitsubishi Electric Corporation assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Mitsubishi Electric Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
- Please also pay attention to information published by Mitsubishi Electric Corporation by various means, including the Mitsubishi Semiconductor home page (http://www.MitsubishiElectric.com/).
- When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
- Mitsubishi Electric Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of Mitsubishi Electric Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
- Any diversion or re-export contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor for further details on these materials or the products contained therein.

© 2011 MITSUBISHI ELECTRIC CORPORATION. ALL RIGHTS RESERVED.